



Rec'd **PL** TO



10/528942

12.09.03




INVESTOR IN PEOPLE

IB03/03987

BEST AVAILABLE COPY

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ



I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

[Signature]

Dated 18 June 2003

PRIORITY DOCUMENT
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH
RULE 17.1(a) OR (b)

30SEP02 E751832-4 003008
P01/7700 0-00-022556.3

Request for grant of a patent
(See notes on the back of this form. You can
also get an explanatory leaflet from the Patent
Office to help you fill in this form)

The Patent Office
Cardiff Road
Newport NP10 8QQ

Your reference PHGB020165

Patent application number
(The Patent Office will fill in this part)

0222556.3

12 8 SEP 2002

Full name, address and postcode of the or of
each applicant (underline all surnames)

KONINKLIJKE PHILIPS ELECTRONICS N.V.
GROENEWOUDSEWEG 1
5621 BA EINDHOVEN
THE NETHERLANDS

Patents ADP Number (if you know it)

75 8 66 05 002

If the applicant is a corporate body, give the
country/state of its incorporation

THE NETHERLANDS

Title of the invention

RF CHIP TESTING METHOD AND SYSTEM

Name of your agent (if you have one)
"Address for service" in the United Kingdom
to which all correspondence should be sent
(including the postcode)

Andrew G. White
Philips Intellectual Property and Standards
Cross Oak Lane
Redhill
Surrey RH1 5HA

Patents ADP number (if you know it)

71 33 47 3003

If you are declaring priority from one or more
earlier patent applications, give the country
and the date of filing of the or of each of these
earlier applications and (if you know it) the or
each application number

Country

Priority Application number
(if you know it)

Date of filing
(day/month/year)

If this application is divided or otherwise
derived from an earlier UK application, give
the number and the filing date of the earlier
application

Number of earlier application

Date of filing
(day/month/year)

Is a statement of inventorship and of right to
grant of a patent required in support of this
request? (Answer "Yes" if:

YES

- a) any applicant named in part 3 is not an inventor, or
 - b) there is an inventor who is not named as an
applicant, or
 - c) any named applicant is a corporate body.
- See note (d))

- Enter the number of sheets for any of the following items you are filing with this form.
Do not count copies of the same document.

Continuation sheets of this form

Description	9
Claims(s)	2
Abstract	1 DML
Drawings	4-5/100

0. If you are also filing any of the following, state how many against each item:

Priority Documents

- Translations of priority documents
Statement of inventorship and right to grant of a patent (*Patents Form 7/77*)
Request for preliminary examination and search (*Patents Form 9/77*)
Request for substantive examination (*Patents Form 10/77*)
Any other documents
(Please specify)

1. I/We request the grant of a patent on the basis of this application.

Signature

[Signature]

Date 27/9/2002

2. Name and daytime telephone number of person to contact in the United Kingdom

01293 815143

(Darren.T. Murley)

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been evoked.

Notes

-) If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
-) Write your answers in capital letters using black ink or you may type them.
-) If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
-) If you have answered "Yes" Patents Form 7/77 will need to be filed.
-) Once you have filled in the form you must remember to sign and date it.
-) For details of the fee and ways to pay please contact the Patent Office.

DESCRIPTION

RF CHIP TESTING METHOD AND SYSTEM

5 The present invention relates to radio frequency (RF) testing methods and further relates to a testing system suitable for practising such methods. The present invention has particular, but not exclusive, application in the testing of the RF functionality of integrated circuit chips and the compliance of such functionality with an intended radio standard or specification.

10 Radio frequency integrated circuit (IC or 'chip') manufacturing requires testing to determine whether the manufactured ICs are compliant with a radio standard (e.g. Bluetooth™, GSM™, IEEE802.15.4) and operational in other respects. Typically, a pick and place machine will place the chip device to be
15 tested in a suitably constructed test board or 'test head' of specialised automated test equipment (ATE). The ATE applies the appropriate test signals to the device under test (DUT) and passes or rejects the device. Such individual chip testing exhibits a problem in that it is time consuming and hence adds to the overall manufacturing cost.

20 Another particular problem in testing the functionality of an RF chip for compliance with a radio standard exists in that the specification may require the ATE to generate several specific analogue RF signals at the same time in order to test, for example, the interference performance of the receiver of the DUT. Special signal generating hardware is therefore required, adding cost to
25 the ATE, and therefore expense to the manufacturer. Furthermore, the application of such signals is often via long probes brought down into contact with the pin-out of the chips, requiring a specially constructed and controlled test suite. The use of such probes results in unspecified and difficult to quantify losses reducing the accuracy of any such test.

30 It is therefore an object of the present invention to provide an improved method and system for RF chip testing.

According to a first aspect of the present invention there is provided a method for testing a plurality of integrated circuit chips for compliance with a radio standard, each chip having transmission means and receiving means for sending and receiving RF signals, the method comprising:

- placing the chips in close proximity to one another,
- testing the transmission means of each chip with respect to a known good reference chip,
- selecting a number of the chips to form a generating group, the remaining chips forming a receiving group, and
- testing the receiving group using signals generated by the generating group.

According to a further aspect of the present invention there is provided a testing system for testing a plurality of integrated circuit chips, each chip having transmission means and receiving means for sending and receiving RF signals, the system comprising:

a computer having communication, control and data acquisition means for communicating with, controlling and acquiring data from testing means to which it is connected,

the testing means comprising a plurality of chip sockets adapted to physically accept and electronically interface with a chip placed therein, and wherein each socket is provided with signal propagation and attenuation means for sending and receiving signals to each of the other sockets under the control of the computer,

and where in operation the computer selects a group of chips to generate test signals which are propagated via the propagation means to a reception test group of chips.

The method and system of the present invention implement applicant's appreciation that many compliance tests in the RF field require a number of signals to be generated, and that the RF chips being tested may be utilised in the system to generate such signals. Hence, a system is provided in which a group of chips, having passed transmission generation tests for example, are

utilised to generate the signals required to test the reception hardware of the other chips.

Preferably, the number of chips selected corresponds to the number of signals required for the particular test. For example, in an interference test a
5 "wanted" signal with two other "interfering signals" must be generated on certain specified channels to determine the quality of the receiver. In such an example test, three chips are therefore required to be selected for the test. If one considers the situation where there are eight chips mounted in the system, then such an interference test requires that three chips are selected (the
10 generating group) to provide the three signals to the remaining five chips (the receiving test group). Following the test, three of the five chips just tested may be selected for the generation group and these then provide the signals to the previous generating group. Hence, such an interference test only requires two "passes" to test all eight chips, and no extra signal generating hardware. This
15 compared with eight individual tests required in a conventional system which in addition requires signal generating hardware to generate the three signals for the above example test, and individual probing (which has the disadvantage of including unknown losses due to such probing).

Advantageously, each chip's signal may be attenuated via
20 programmable attenuators before being provided to the test group of chips. This allows for imbalance in transmission and reception power required for a test. For example the Bluetooth specification requires a transmission power of 0dBm whilst the chips receiving hardware requires a signal of the order of -70dBm, therefore the signals generated by the group of chips require 70dB
25 attenuation.

In a preferred embodiment, the computer is a standard PC with a digital data acquisition card to interface it to the test board. The control and test routines and analysis of data captured by the card are provided in software. Hence this digital test equipment is relatively inexpensive and flexible enabling
30 different tests for different radio specifications to be installed or downloaded as required by the customer.

The present invention will now be described, by way of example only, and with reference to the accompanying drawings wherein:

Figure 1 is a block diagram of the circuitry of an RF chip being a device under test (DUT);

5 Figure 2 is a schematic diagram of a system for testing a chip as shown in Fig. 1;

Figure 3 is flow diagram representing example steps of a method embodying the invention;

10 Figure 4 is another flow diagram representing example steps of a method embodying the invention in which intermodulation and other receiver tests are performed.

15 It should be noted that the Figures are diagrammatic and not drawn to scale. Relative dimensions and proportions of parts of these Figures have been shown exaggerated or reduced in size, for the sake of clarity and convenience in the drawings. The same reference signs are generally used to refer to corresponding or similar features in modified and different embodiments.

20 Figure 1 shows a typical transceiver architecture for an RF chip. This architecture comprises a baseband section 10 connected with a transmission chain 20 comprising a digital to analog converter (DAC) for converting the intended digital signal to an analogue signal, a mixing stage where the signal is mixed with the output of a frequency synthesiser block 22 and a power amplifier for amplifying the resulting signal. A receiving chain 30 comprises an antenna filter, a low noise amplifier, a mixing stage, channel filtering and demodulating stage. Such a general transceiver having transmission and reception means for generating and transmitting/receiving signals is well known to those skilled in the art. In an application, for example a mobile phone or personal digital assistant (PDA), the transceiver is connected to an antenna for radiating or receiving radiated signals. In a testing environment, prior to incorporation in a final product such as a mobile phone, the transceiver (Tx) 20 and receiver (Rx) 30 blocks are connected to relevant pins of the chip

(if packaged) or a pad/probe applied to the appropriate test location on the silicon die containing the transceiver circuitry (if testing is prior to packaging).

An integrated circuit for producing for example, Bluetooth signals may do so via such an architecture as shown in Fig. 1, together with a layered protocol. The Bluetooth protocol or specification as laid out in the Bluetooth specification v1.1 requires the radio performance of such a chip to meet certain test requirements. Pages 20-32 of the aforementioned specification, which are incorporated herein for reference and to which the reader is now directed, specify among others the following tests: output power and power control of the transmitter, sensitivity, interference performance, intermodulation characteristic and receiver signal strength indicator.

It is to be noted that several of these tests require a number of signals to be generated at the same time. In particular, characterisation of the receiver for interference performance involves co-channel and adjacent channel tests which each require two transmission signals to be generated. The characterisation and testing of the intermodulation characteristics of the receiver require three signals to be generated - a wanted signal at a first frequency f_0 with a power level 6dB over the reference sensitivity level, a static sine wave signal at another frequency f_1 with a power level of -39 dBm and a bluetooth modulated signal at a further frequency f_2 with a power level of -39dBm, such that $f_0 = 2f_1 - f_2$ and $\text{mod}(f_2 - f_1) = n \cdot 1 \text{ MHz}$ where n can be 3, 4, or 5. In general the Bit Error Rate (BER) is measured and evaluated against a predetermined level (e.g. 0.1%) to provide a pass/fail for these tests.

Figure 2 is a diagram of a digital testing system embodying the present invention. The system comprises a computer in the form of a PC 40 having a display and a digital acquisition card (DAQ) 55, a suitable example being National InstrumentsTM PCI 7030/6030E. Testing routines, control and analysis software are provided with the computer on suitable media 60, or may be downloaded over a suitable internet link (not shown). The computer and DAQ are connected to a test board or "test head" 80 via a SCSI link 70 although other suitable interface links 70 may be used (IEEE1394 'Firewire', and USB being common examples).

The board 80 comprises in this embodiment eight chip sockets 82a,b,c (labelled X1,X2 to X7, and GS in the diagram) for accepting radio chips for testing. Each socket interfaces electronically (via techniques well known in the art such as tensioned pins or solderbump pads) with the chip mounted therein.

5 Suitably designed tracks 88 with programmable attenuators 86 (A1 to A7, A_{gs}) for interconnecting and propagating signals from one chip socket to another are provided. Control and input/output (I/O) data is passed between the computer 40 and sockets via the test head link 70. In this embodiment the socket 82c is provided for a "golden sample" chip. This chip has been

10 previously tested and characterised and is used as a reference with which to compare the characteristics of other chips just manufactured.

Figure 3 illustrates a flow chart example of a testing method performed by the system of Figure 2, and as implemented by software 60. In the method chips are loaded into sockets 82a,b. The golden sample socket 82c is loaded

15 with a golden sample. In the basic method according to the invention the transmission circuitry 20 of each chip is tested (step 100) with respect to the golden sample. For example the power output of each transceiver may be measured and compared with the known golden sample power output which is within the specified Bluetooth requirements. After testing all of the loaded

20 chips X1-X7, the computer determines (step 102) whether the result was a pass or fail for each chip and stores the result in memory. The testing then moves onto testing the receiver chain 30 of each chip for specification compliance.

In step 104 the computer selects a first group of chips (for example the

25 chips mounted in sockets X5, X6 and X7 as denoted by the dashed box labelled 82b in Figure 2) which will form a signal generating group for generating the signals which must be received by the remaining test chips 82a in order to test the receiver circuitry 30 of those remaining chips. Under the control of the computer the receiving group of chips are each subjected to the

30 signals generated by the first group, thereby testing the receiver circuitry 30 of those chips in parallel (step 106). In this embodiment, the transmitted signals from X5, X6 and X7 are attenuated by the programmable attenuators A5, A6,

A7 and then passed down signal propagation tracks 88 to the receiver test group 82a of X1, X2, X3 and X4. Following step 106, the generating group becomes a receiving group to enable testing of the receiver circuitry of those chips, and a new second generating group is selected ('SEL 2G' step 108) to generate the test signals. The receiving group (which acted as the first generating group previously) is subsequently tested in step 110 and the results from the tests analysed.

Hence, RF analogue signals which are required for testing the receiver functionality of a radio chip are generated "on-board" by a group of chips which themselves form part of the test. Additionally, the signals are routed to the test chips in parallel, hence saving time and effectively testing the receiver group of chips instantaneously.

Figure 4 illustrates a flowchart giving a particular example of testing requirements which are necessary for evaluating a BluetoothTM radio chip and wherein a methodology embodying the invention is applied. In this particular example seven chips labelled X1 to X7 are to be tested with respect to a golden sample for transmission characteristics (power output and control) and receiver characteristics (intermodulation, co-channel, adjacent channel, sensitivity and Receiver Signal Strength Indicator (RSSI)), wherein:

- block 120 - IC's X_i ($i=1$ to 7) are loaded as is the golden sample chip, following which;
- block 122 - IC X_i transmits a signal s_i at a first frequency f_1 to the golden sample chip, and attenuator A_i is programmed to reduce the power of signal s_i , after which;
- in block 124 the BER of the signal s_i as received by the golden sample is analysed and a decision is made as to whether the transmitter of X_i is either:
 - not within specification (block 126), X_i is characterised as a reject and is not included in any further tests,
 - or is within specification, the result is stored and
- in block 128, a determination is made (is $i < 7$?) whether all chips have been tested. If there are still chips to be tested then $i=i+1$ and the

program flow follows path 130 back to block 122. Once all chips have been tested ($i=7$) then the program flow moves to the next required tests in block 132;

- 5 • Block 132 - Intermodulation tests are performed to determine receiver characteristics. X1, X3 and X3 selected to provide a wanted signal, an interfering signal and a co-channel signal respectively. A1, A2 and A3 are programmed to limit outputs;
- 10 • Block 134 - the signals are provided by X1, X2 and X3 to the remaining chips X4, X5, X6 and X7 and the results analysed for each IC as to whether it:
 - Fails - block 136 - IC is rejected as receiver not within specification
 - Or passes in which case flow moves to
- 15 • Block 138 wherein X4, X5 and X6 are selected to generate the intermodulation test signals and A4, A5 and A6 programmable attenuators are programmed to limit outputs, following which:
- 20 • Block 140, the signals are provided by X4, X5 and X6 to the remaining chips X1, X2, X3 and the results analysed for each IC as to whether it:
 - Fails - block 142 - IC is rejected as receiver not within specification
 - Or passes in which case flow moves to
- 25 • Block 144 wherein the remaining RF tests (co-channel, Adjacent channel, sensitivity and RSSI calibration are performed on those chips which have previously passed the transmitter tests (block 124) and the intermodulation receiver tests (blocks 134 and 140) after which
- 30 • those IC which have passed all tests are noted as being within test specification requirements.

In the above embodiments an example testing system and methods were described with reference to packaged Bluetooth™ radio chips.

- 30 In an alternative embodiment the sockets for accepting chips are replaced with suitably designed solder pads on which singulated die may be placed. Testing may then be executed as described previously. Hence, in this

embodiment a manufacturer is able to test integrated circuit chips in the form of singulated die before packaging, thereby enabling faster quality testing "upstream" of the packaging process.

Those skilled in the art of testing will recognise that implementing the example testing flow charts of Fig. 3 and Fig. 4 is a matter of software design for the digital testing equipment designer. The overall software control, interfacing and analysis aspects of the testing system may be routinely implemented by those skilled in the art of designing and building test heads and testing systems. Other well known features of automatic testing equipment, such as a "pick and place" machine for handling and loading/unloading chips from the test head, and the marking of chips with ink in the event of a test failure, although not mentioned in the above embodiments, will be recognised as being compatible with the above.

Furthermore, in the foregoing embodiments, the method and system aspects of the present invention were described as applied to packaged chips or singulated die IC, the IC being a Bluetooth™ compatible design. Those skilled in the art will recognise that the testing method and systems aspects of the present invention can readily be applied to other different radio chips requiring confirmation of conformity with a particular specification for which those chips are designed. Many radio chips require testing for so-called "front end linearity," with the radio specification specifying the linearity and absolute standards required. For example, radio standards such as IEEE802.15.4 ('ZigBee'), 'GSM', and the so called '3G' telephony standards require radio chips which can benefit from specification testing equipment and methods embodying the present invention.

From reading the present disclosure, other modifications will be apparent to persons skilled in the art. Such modifications may involve other features which are already known in the design, manufacture and use of RF testing systems, test heads and component parts thereof and which may be used instead of or in addition to features already described herein without departing from the spirit and scope of the present invention.

CLAIMS

1. A method for testing a plurality of integrated circuit chips for compliance with a radio standard, each chip having transmission means and receiving means for sending and receiving RF signals, the method comprising:
- placing the chips in close proximity to one another,
 - testing the transmission means of each chip with respect to a known good reference chip,
 - selecting a number of the chips to form a generating group, the remaining chips forming a receiving group, and
 - testing the receiving group using signals generated by the generating group.
2. A method according to claim 1, wherein the chips are mounted on a test board prior to testing.
3. A method according to claim 1 or claim 2, wherein the selection of generating and receiving groups is repeated until all chips have been tested.
4. A method according to claim 1, wherein the number of chips selected to form a generating group is determined at least in part by the testing requirements.
5. A method according to claim 4, wherein the testing requirements specify a test requiring at least two generated signals.
6. A method according to claim 4, wherein the testing requirements specify an intermodulation test requiring three generated signals.
7. A testing system for testing a plurality of integrated circuit chips, each chip having transmission means and receiving means for sending and receiving RF signals, the system comprising:
-

a computer having communication, control and data acquisition means for communicating with, controlling and acquiring data from testing means to which it is connected,

the testing means comprising a plurality of chip sockets adapted to
5 physically accept and electronically interface with a chip placed therein, and wherein each socket is provided with signal propagation and attenuation means for sending and receiving signals to each of the other sockets under the control of the computer,

and where in operation the computer selects a group of chips to
10 generate test signals which are propagated via the propagation means to a reception test group of chips.

8. A system according to claim 7, wherein the sockets are located
on a test board.
15

9. A system according to claim 7 or claim 8, wherein the signals
generated by the selected group are radio frequency signals.

10. A test board comprising a plurality of chip sockets adapted to
20 physically accept and electronically interface with a chip placed therein, and wherein each socket is provided with signal propagation and attenuation means for sending and receiving test signals generated by at least one chip to each of the other sockets.

25 11. A computer program comprising instructions for performing a method according to claim 1.

12. A computer readable storage medium having recorded thereon
data representing instructions for performing a method according to claim 1.
30

ABSTRACT

RF CHIP TESTING METHOD AND SYSTEM

5 A method and system for testing RF chips for radio specification compliance is described. The system comprises a test board (80) having a plurality of interconnected sockets (82a,b,c) for receiving chips to be tested. In testing, signals generated by transmitter circuitry (20) within a group of test chips are used to test the receiver (30) functionality of the other chips loaded
10 in the system. Hence, for tests requiring several analogue radio signals, a plurality of chips are tested at the same time using signals generated from other chips. Additionally, the system does not require expensive dedicated RF analogue signal generating equipment.

15 [Figure 2]

1/4




Fig. 1




Fig. 2

3/4




Fig. 3

4/4




Fig. 4

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ **BLACK BORDERS**
- ☒ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☒ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☒ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.